

Syscompact 400

BAUR cable fault location system



The figure is illustrative

Compact and multifunctional

- Easy to operate
- High-performance surge voltage generator
- Proven fault pre-location methods
- Maximum safety during application

The compact cable fault location system, Syscompact 400, is used for the pre-location and pin-pointing of faults on power cables. It is easy to transport and is also suitable for installation in any small van with a payload of 300 – 500 kg.

Thanks to Wi-Fi connectivity, the time domain reflectometer can be operated remotely. With the integrated CAT IV/600 V separation filter, TDR measurements can also be performed safely on live cables. User-friendly menu navigation in multiple languages and proven fault location methods ensure fast and precise measurement results.

When combined with the separately available BAUR protrac® pin-pointing system, it is possible to pin-point cable faults acoustically and to pin-point cable sheath faults with the step voltage method.

NEW: BAUR Fault Location App

Functions

- TDR: Time Domain Reflectometry (1- and 3-phase)
- Step TDR for the pre-location of cable faults and joints in the vicinity (1- and 3-phase) – only with the BAUR BUI-F app
- SIM/MIM: Secondary/multiple impulse method
- DC-SIM/MIM: Secondary/multiple impulse method used in DC mode
- ICM: Impulse current method
- DC-ICM: Impulse current method used in DC mode
- Decay method (option)
- Cable and cable sheath testing up to 32 kV

Features

- Measurements carried out via:
 - Laptop with BAUR Software 4 or
 - Tablet with BAUR BUI-F app
- In the case of control via laptop: Transfer of relevant cable route data to the BAUR Fault Location App to assist with cable fault pin-pointing
- Surge energy up to 2,050 J
- Long service life of the electrodes thanks to optimised physical properties
- High reliability of the spark gap
- Easy maintenance and repair by trained personnel on site
- Length-dependent gain for better display of remote events
- Compact system, suitable for installation in a small van

Technical data

IRG 400 time domain reflectometer	
Pulse voltage	60 V
Pulse width	30 ns – 10 µs
Number of pulses (SIM/MIM)	1 – 20 pulses, adjustable
Voltage-proof up to	400 V, 50/60 Hz
Measurement category	CAT IV/600 V (with enabled separation filter)
Input signal gain	Dynamic range 101 dB (-63 to +38 dB) +40 dB (length-dependent gain)
Measurement range	10 m – 250 km
Accuracy	0.1% (relating to the measurement result)
Data rate	400 MHz
Resolution	0.1 m (at v/2 = 80 m/µs)
Velocity of propagation (v/2)	20 – 150 m/µs, adjustable
Control	▪ Via laptop with BAUR Software 4 ▪ Via tablet with BAUR BUI-F app

Surge voltage generator	
Surge voltage ranges	0 – 8 kV, 0 – 16 kV, 0 – 32 kV
Surge energy	SSG 1100 1,100 J SSG 1500 option 1,540 J SSG 2100 option 2,050 J
Surge sequence	10 or 20 pulses/min, single surge SSG 1500 option 20 or 30 pulses/min, single surge
DC voltage	0 – 32 kV
Max. output current (burn)	DC 560 mA (0 – 8 kV)
SSG 1500 / SSG 2100 option	DC 850 mA (0 – 8 kV)

Surge capacitor extension	SZ 1000	SZ 1600
Surge voltage range	0 – 4 kV	0 – 4 kV
Surge energy		
SSG 1100	880 J	1,480 J
SSG 1500 option	980 J	1,580 J
SSG 2100 option	1,110 J	1,710 J

System	
Power supply	220 – 230 V, 50/60 Hz
Other power supplies optional	See "Standard delivery, accessories and options"
Ambient temperature (operational)	-10°C to +50°C
Storage temperature	-20°C to +60°C
Dimensions incl. KTG M3 cable drum rack (W x H x D)	Approx. 935 x 970 x 775 mm
Weight	From 195 kg (depending on configuration)
Degree of protection	IP21
Safety and EMC	CE-compliant in accordance with Low Voltage Directive (2014/35/EU), EMC Directive (2014/30/EU), EN 60068-2-ff Environmental testing

Standard delivery, accessories and options

Syscompact 400		
IRG 400 time domain reflectometer incl. laptop with pre-installed BAUR Software 4 (cable fault location)		✓
Options for BAUR Software 4 See "Optional software functions for BAUR Software 4"		
IRG 400 time domain reflectometer incl. tablet with BAUR BUI-F app installed		Option
Surge voltage generator:		
	SSG 1100	✓
	SSG 1500	Option
	SSG 2100	Option
Surge capacitor extension:		
	SZ 1000	Option
	SZ 1600	Option
Power supply:		
	220 – 230 V, 50/60 Hz	✓
	110/230 V, 50/60 Hz, 1.5 kVA, via external auto transformer	Option
	110/230 V, 50/60 Hz, 3.0 kVA, via external auto transformer	Option
	Isolation transformer with protective earthing connection, 2.5 kVA	Option
SA 32 SIM/MIM coupling unit		✓
SK 1D inductive coupler for ICM		✓
19" rack, height 21 RU (933.45 mm), depth 700 mm		✓
Jumper plug for external emergency off unit		✓
KTG M3 cable drum rack incl.		✓
- CS 2 HV connection socket, 40 kV - HV connection cable, mains supply cord, and earth cable, each of 25 m cable length - Contact monitoring of the earth terminal		
KTG M3 cable drum rack incl.		Option
- CS 2 HV connection socket, 40 kV - HV connection cable, mains supply cord, and earth cable, each of 50 m cable length - Contact monitoring of the earth terminal		
TDR connection cable, CAT IV/600 V, 3-phase, 25 m or 50 m cable length, on hand cable drum		Option
GR 40 earth rod		✓
GDR 40-250 discharge and earth rod		Option
External emergency off unit with signal lamps, 25 m or 50 m cable length		Option
Trolley for Syscompact 400		Option
Steel frame with wheels and guide rods for Syscompact 400		Option
Steel pallet for Syscompact 400		Option
User manual		✓

- ✓ Included in standard delivery
Option Optionally available

Optional software functions for BAUR Software 4

- Mapping* (available countries on request)
- GIS interface*
- BAUR Fault Location App*
- BAUR Software 4 for office PC (office installation)

* These optional software functions are only available when the IRG 400 time domain reflectometer is controlled via a laptop and the BAUR Software 4.



Example: Map view in the BAUR Fault Location App
(only available when control is via laptop and BAUR Software 4)



Would you like to discover more about this product?
If so, contact us: www.baur.eu > **BAUR worldwide**